FX0342 Datasheet

Product Name // Fuseholder Protection Category PC1 PCB Mount 2 PCB Spills 5mm x 20mm Fuse Screw Cap Carrier Hand Release

View Product Page



Image not found or type unknown

// Product Description:

- PCB Mount Protection Category PC3 Fuseholders
- 5mm x 20mm fuse carrier, Screw Cap, Hand Release
- Choice of Termination, depending on part code:
  - FX0342: Two PCB Spills
  - FX0330: Three PCB Spills (twin PCB Spills at rear)

// General Information:

Product Display Title:	PCB Mount Protection Category PC3 Fuseholders
Product Family:	Fuseholders
Product Series:	PC Mounting PC1, PC2 and PC3
Body Material:	Nylon 66 - Glass Filled
Current Max:	6.3A
Flamability Rating:	UL94V-0
Function:	Pc1 Fuseholder
Fuseholder Mounting Hole:	2 or 3 Mounting Holes
Fuseholder Protection Category:	PC1
Fuse Carrier:	Screw Cap/Hand Release
Fuse Size:	5mm x 20mm
Max Operating Temperature:	+85°C
Min Operating Temperature:	-20°C
Voltage Max:	250V

// Product PDF Links

Fuseholders product data

// Product 3D CAD Model Links

FX03423D CAD Model